

ALFATRON ALF-120W-UB 120W Mixer Amplifier



DESCRIPTION

ALFATRON ALF - 120W-UB Mini Mixer Amplifier with MP3 Player, FM Radio and Bluetooth. It includes a remote controller.

FEATURES

- Compact public-address amplifier.
- Speaker output of 100V or 70V & 4 -16 ohms, rated power output of 120W.
- Built in Mp3 player, FM radio & Bluetooth with remote controller.
- 2 MIC inputs, 1 EMC input, 2-line inputs, 1-line output.
- Built in Class-D amplifier module and switching power, with 100V/70V transformer technology.
- Individual volume control for Mic 1-2, Aux 1-2, bass/treble and master volume control.
- Support both AC100-240V & DC 24V power supply.
- Priority: EMC > MIC1 > others.
- LED indicators for power, clip, protect and signal.
- With short-circuit, clip, overload and high temp protection.
- Ideal for small venues such as classrooms, retail stores, coffee shops, restaurants etc

TECHNICAL SPECIFICATIONS

Specification	
Rated Power	120W
Speaker Outputs	100V or 70V & 4 Ohms - 8 Ohms-16 Ohms
Connector	Mic1 input by Unbalanced Jack Mic2 Balance XLR Socket Line 1-2 inputs by RCA: Line output by RCA
Attenuation	Microphone 1-2, Line 1-2 and Mp3/FM, bass/treble and master
MIC1 - 3 input Sensitivity	5mV
AUX1 & 2 input Sensitivity	350mV
EMC input Sensitivity	350mV
MIC Frequency response	180Hz - 10kHz (+- 3dB)
AUX Frequency response	70Hz -16Hz (+- 3dB)
Noise	< 5mV (4 Ohm load output terminal)
THD	< 1% 1KHz
Protection	Short Circuit, Clip Overload and high Temp protection
Treble adjustment	10dB (+-2)
Bass adjustment	10dB (+-2)
Rated Power Supply	AC-110-220V
Rated output voltage	60W/4 Ohm, AC220V
Priority	EMC>MIC1> Others
Dimensions	247 x 198 x 66mm
Packaging Size	343 x 302 x 121mm
Net Weight	2.6Kg